

18TLW3000

Extended LF Ferrite Transducer

3600 W program power handling

100 mm (4 in) Tetracoil dual voice coil, equivalent to a single coil diameter larger than 152 mm (> 6 in)

Ultra linear suspension behavior for excellent sound clarity

Symmetric flux density and inductance behaviour

Low noise forced air cooling design

Water repellent cone and epoxy coated plates for outdoor use Suitable for vented, horn loaded and bandpass subwoofer design

GENERAL SPECIFICATIONS

Nominal Diameter	460 mm (18 in)
Rated Impedance	8 Ohm
AES Power (1)	1800 W
Program Power (2)	3600 W
Peak Power	10000 W
Sensitivity (3)	95 dB
Frequency Range (4)	30 - 2000 Hz
Power Compression @-1 OdB	0,6 dB
Power Compression @-3dB	2,0 dB
Power Compression @Full Power	3,4 dB
Max Recomm. Frequency	300 Hz
Recomm. Enclosure Volume	100 - 350 lt. (3,53 - 12,36 cuft)
Minimum Impedance	5,7 Ohm at 25°C
Max Peak To Peak Excursion	45 mm (1.77 in)


THIELE SMALL PARAMETERS (5)

Fs	33 Hz
Re	4,6 Ohm
Sd	0,1225 sq. mt. (189,88 sq. in.)
Qms	13,00
Qes	0,42
Qts	0,41
Vas	185 lt. (6.53 cuft)
Mms	266 gr. (0,59 lb)
BL	24,5 Tm
Linear Mathematical Xmax (6)	± 12 mm (± 0,47 in)
Le (1kHz)	1,80 mH
Ref. Efficiency 1W@1m (half space)	94,0 dB

MOUNTING INFORMATION


Overall diameter	462 mm (18,18 in)
N. of mounting holes and bolt	8
Mounting holes diameter	8,5 mm (0,33 in)
Bolt circle diameter	438-440 mm (17,24-17,32 in)
Front mount baffle cutout ∅	425 mm (16.73 in)
Rear mount baffle cutout ∅	414 mm (16,30 in)
Total depth	275 mm (10,83 in)
Flange and gasket thickness	24 mm (0.94 in)
Net weight	13,2 kg (29.10 lb)
Shipping weight	14 kg (30.86 lb)
CardBoard Packaging dimensions	482 x 482 x 257 mm (19 x 19 x 10,1 in)

FREQUENCY RESPONSE CURVE



FREQUENCY RESPONSE MADE IN 180 IT. ENCLOSURE TUNED AT 35 Hz IN FREE FIELD (4p) ENVIRONMENT. ENCLO-SURE CLOSES THE REAR OF THE DRIVER, THE THIN LINE REPRESENTS 45° OFF AXIS FREQUENCY RESPONSE

FREE AIR IMPEDANCE MAGNITUDE CURVE



FREE AIR IMPEDANCE MAGNITUDE CURVE

NOTES

- (1) AES power is determined according to AES2-1984 (r2003) standard (2) Program power rating is measured in 180 lit enclosure tuned 35Hz using a 40 400Hz band limited pink noise test signal with 50% duty cycle, applied for 2 hours.
- (3) Sensitivity represents the averaged value of acoustic output as measured on the forward central axis of cone, at distance 1m from the baffle panel, when connected to 2,83V sine wave test signal swept between 100Hz and 500Hz with the test specimen mounted in the same enclosure as given for (1) above.
- (1) doore.

 (4) Frequency range is given as the band of frequencies delineated by the lower and upper limits where the output level drops by 10 dB below the rated sensitivity in half space environment.

 (5) Thiele Small parameters are measured after the test specimen has been conditioned by 1 hour
- (5) Thiele Small parameters are measured after the test specimen has been conditioned by 1 hour 20 Hz sine and represent the expected long term parameters after a short period of use.
- (6) Linear Math. Xmax is calculated as (HvcHg)/2 + Hg/4 where Hvc is the coil depth and Hg is the gap depth.